

**Amplicon.com** 

IT and Instrumentation for industry



Sales: +44 (0) 1273 570 220 Website: www.amplicon.com Email: sales@amplicon.com

## **Datasheet**

## **Major Features**

- Supports CAN FD, up to 8 Mbit/s (with correct physical layer implementation).
- Quick and easy plug-and-play installation.
- Supports both 11-bit (CAN 2.0A) and 29bit (CAN 2.0B active) identifiers.
- Compatible with applications written for other Kvaser CAN hardware with Kvaser CANlib.
- High-speed CAN connection (compliant with ISO 11898-2), up to 1 Mbit /s.
- Designed to be compatible with J1939, CANopen, NMEA 2000® and DeviceNet. Higher Layer protocol stacks are not included.
- Simultaneous operation of multiple devices.
- Low profile board, includes low and high profile brackets.
- Includes 4 channel breakout cable.

## **Software**

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at www.kvaser.com/downloads.

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types.

## Technical data

Bus Interface	PCIe x1
CAN Bit Rate	20 kbit/s to 1 Mbit/s
CAN Channels	4
CAN FD	Yes
CAN Transceivers	MCP2561FD
Certifications	CE, RoHS
Connector	HD DSUB 26
Dimensions	Low profile, 86 x 69 mm
Error Frame Detection	Yes
Error Frame Generation	Yes
Galvanic Isolation	Yes
Operating Systems	Windows, Linux
Operating Temperature Range	-40 °C to +85 °C
Power Consumtion	700-1300 mW
Silent Mode	Yes
Timestamp Resolution	1 μs
Weight with cable	200 g

Amplicon.com

IT and Instrumentation for industry

